# TX-NR727 7.2-Channel Network A/V Receiver

BLACK SILVER

ONKYO







### Transform Your Days and Nights with THX<sup>®</sup> Entertainment

Extract every last drop of performance from your home cinema budget with the THX<sup>®</sup> Select2<sup>™</sup> Plus-certified TX-NR727. Three-Stage Inverted Darlington Circuitry for all seven channels ensures reference-level playback of your hi-res media. DSX® surround expansion, MultEQ® speaker calibration, and real-time Dynamic EQ® technology—all from class-leader Audyssey—treat the listener to a cinematic experience that's so realistic you can almost smell the popcorn. For music lovers, built-in Wi-Fi allows you to stream 192/24 hi-res, lossless, and compressed audio directly from smartphone and tablet, or from PC and NAS using our remote app to control playback. The app also enables quick selection of internet radio and streaming service channels. Or, if you prefer, simply pair and stream using onboard Bluetooth technology. To expand beyond the living room, a selection of powered outputs and line-outs are on hand for synchronized audio in up to three zones around the home. With eight 4K- and 3D-ready HDMI® inputs, two outputs (one with ARC), and 4K video upscaling via Qdeo<sup>™</sup> technology, the TX-NR727 takes its place at the very top of the class.

#### ADVANCED FEATURES

- THX<sup>®</sup> Select2<sup>™</sup> Plus-Certified for Studio Reference Playback
- HDMI<sup>®</sup>Video Upscaling to 4K with Qdeo<sup>™</sup> Processing Technology by Marvell
- 4K Passthrough from Compatible Source Devices via HDMI
- Built-in Wi-Fi-Certified Wireless LAN Capability
- Bluetooth Version 2.1 + EDR Capability (Compatible
- Profile: A2DP v1.2, AVRCP v1.3)
- Three-Stage Inverted Darlington Circuitry with Discrete Output Stage for All Channels
- Frontside MHL<sup>™</sup> for 1080p Video and Stills from
- Smartphone and Tablet
- Internet Radio and Music Streaming Service Connectivity
- (TuneIn Radio, Last.fm, Spotify, AUPEO!, and Simfy)\*1
- Playback of Audio Files Over Wireless Home Network (MP3, WMA, WMA Lossless, FLAC, WAV, Ogg Vorbis,
- AAC, Apple Lossless, DSD, LPCM<sup>\*2</sup>, and Dolby<sup>®</sup> TrueHD)
- Supports Onkyo Remote Apps for iPod touch/iPhone\*3 and Android Devices\*4
- Picture-in-Picture Input Video Preview with InstaPrevue<sup>1</sup> Technology
- Phase-Matching Bass Boost
- Audyssey MultEQ® for Room Acoustic Correction
- Audyssey DSX<sup>®</sup> and Dolby<sup>®</sup> Pro Logic<sup>®</sup> IIz Upmixing
- for Seven-Channel Surround Sound • Overlaid On-Screen Display (OSD) via HDMI with
- Quick Set-Up and Home Menu Powered Zone 2 and Zone 2/3 Line-Out for Distributed 
  Pure Audio Mode
- Audio Playback in Multiple Rooms
- Hybrid Standby Power-Saving for Video and Network
- Connectivity in Standby • Smart Grid-Ready

• Bi-Amping Capability for Front Channels

\*I Availability of services depends on region. Some services may require a to Availabili of third-b vices advertised here is accurate are uha \*2 I PCM is a

#### AMPLIFIER FEATURES

- 170 W/Ch (6 Ω, 1 kHz, 1% THD, 1 Channel Driven,
- IEC);185 W/Ch (6 Ω, 1 kHz, 1 Channel Driven, [EITA)
- WRAT (Wide Range Amplifier Technology) • H.C.P.S. (High Current Power Supply) Massive High-
- Power Transformer
- Discrete Output Stage Circuitry
- Optimum Gain Volume Circuitry
- PLL (Phase Locked Loop) Jitter-Cleaning Circuit Technology for S/PDIF Audio

#### PROCESSING FEATURES

- HDMI Support for 3D, Audio Return Channel, DeepColor<sup>™</sup>, x.v.Color<sup>™</sup>, LipSync, Dolby TrueHD, DTS-HD Master Audio<sup>™</sup>, DVD-Audio, Super Audio CD, Multichannel PCM, and CEC
- TI Burr-Brown 192 kHz/24-Bit DAC for All Channels
- Advanced 32-Bit Processing DSP Chip
- 4 DSP Modes for Gaming: Rock, Sports, Action, and RPG
- Advanced Music Optimizer for Compressed Digital Music
- Theater-Dimensional Virtual Surround Function
- Direct Mode
- Double Bass Function
- Non-Scaling Configuration
- A-Form Listening Mode Memory


#### CONNECTION FEATURES

- 8 HDMI Inputs (1 Front/7 Rear) and 2 Outputs • Front-Panel USB Port for Mass Storage Class Devices
  - (Wide Selection of File Formats Supported)
- HDTV-Capable (720p/1080i) Component Video
- Switching (I Input and I Output)
- 4 Composite Video Inputs and 1 Output • 3 Digital Audio Inputs (1 Optical and 2 Coaxial)
- 6 Analog Audio Inputs
- Phono Input for Turntable Connection
- 2 Parallel Subwoofer Pre-Outs Color-Coded, Banana Plug-Compatible Speaker Posts
- Headphone lack

#### OTHER FEATURES

- Audyssey Dynamic EQ® for Loudness Correction
- Audyssey Dynamic Volume<sup>®</sup> Listening-Level Adjustment
- Independent Crossover Adjustment for Each Channel
- (40/50/60/70/80/90/100/120/150/200 Hz) • A/V Sync Control (Up to 800 ms in 10 ms Steps at 48 kHz)
- Tone Control (Bass/Treble) for Front L/R Channels
- · 3-Mode Display Dimmer (Normal/Dim/Dimmer.
- Volume Knob LED: On/Off)\* • RDS (PS/RT/PTY/TP) (European Model Only)
- 40 FM/AM Random Presets
- Certified with DI NA Version 1.5
- Firmware Updates via Network and USB
- Aluminum Volume Control Knob
- Compatible with RI Dock for iPod/iPhone and AirPlay (DS-A5)
- RIHD (Remote Interactive over HDMI) for System Control





- Preprogrammed RI (Remote Interactive) Remote Control
- \*Note: Volume knob LED is always off when display is d



## TX-NR727 7.2-Channel Network A/V Receiver

#### THX<sup>®</sup> Select2<sup>™</sup> Plus for Reference-Level Sound

To be awarded THX Select2 Plus certification—the most rigorous performance benchmark for this type of productthe home cinema receiver must play at studio reference volume levels with minimal distortion. Select2 Plus is specified for screen-to-seat distances of three to four meters and room volumes of about 56 cubic meters.

#### Wi-Fi and Bluetooth Streaming Technology

The TX-NR727 connects to the wireless home network without LAN cables or adapters. Send a huge range of hires, lossless, and compressed files to your home cinema from smartphone, PC, tablet, NAS, and online sources using our remote control app. Or pair devices for quality wireless streaming using the built-in Bluetooth technology

#### Music Streaming and Internet Radio Services

The TX-NR727 comes preloaded with popular music streaming and internet radio services including Spotify Last. fm, and Tuneln Radio. They're easily selectable using the receiver's GUI or the remote control app. Explore more than 10.000 radio stations and enjoy albums and playlists with theater-fidelity sound.

Note: Availability of services depends on region. Some services may require a subscription and a firmware update. Availability of services advertised here is accurate at the time of publication, but may be subject to change without no

#### HDMI® for High Resolution Playback

The TX-NR727 features eight HDMI inputs to accept hi-res content from your media players and gaming consoles. HDMI enables Dolby® TrueHD and DTS-HD Master Audio™ audio formats, and supports 3D video. Two outputs are included to connect your HDTV and video projector.

#### Supports 4K Video Content

With 4K televisions, media players, and projectors hitting the market, it's reassuring to know your A/V receiver is compatible with this new technology. Passthrough of native 4K from source devices to an appropriate display is supported.

#### 4K Video Upscaling via Qdeo<sup>™</sup> Technology

The TX-NR727 uses Qdeo™ technology from Marvell to upscale standard video sources to brilliantly smooth 1080p (for regular HDTVs) and to an incredible 4K on compatible displays.

#### MHL<sup>™</sup> for Mobile Phones and Tablets

A frontside HDMI/MHL terminal is included to connect smartphones and other electronic devices. MHL allows you to display 1080p video and other media on your HDTV with 7 L channels of surround sound

#### Quick and Easy Remote App Control

Our remote apps for iPhone and Android devices offer a convenient way to control your entertainment from anywhere within wireless range. The app offers a clear interface for managing content, settings, and playback across multiple zones.

#### Hassle-Free Video Switching

Switching between games, movies, and cable TV should be easy. InstaPrevue™ technology names your HDMI devices and displays video thumbnails of available content. Now you can switch sources without having to remember what device is connected where.

#### Overlaid Menus for Quick Adjustments

Touch the Ouick Set-Up button on your remote to overlay menus in-program. You can now access useful settings without interruption to your viewing. The Home Menu, meanwhile, offers simple icons for choosing a media source, and more detailed system adjustment.

#### An Introduction to High-End Sound Quality

Onkyo's WRAT (Wide Range Amp Technology) includes discrete low-negative-feedback amplifiers for punchy, true-tolife sound; closed ground-loop circuits to reduce noise; and high instantaneous current to counter impedance fluctuations. Three-Stage Inverted Darlington Circuitry is used on all channels to handle reference-level playback without distorting.

#### Audyssey MultEQ®

MultEQ equalizes your system to suit the unique shape of your room. Measuring six listening positions. MultEO applies filters to satellites and subwoofers to create a perfectly balanced soundstage.

#### Audyssey Dynamic EQ®

Dynamic EQ solves the problem of deteriorating sound quality at low volume. It selects the best frequency response and surround levels moment-by-moment, resulting in an optimal listening experience at any volume.

#### Audyssey Dynamic Volume®

Audyssey Dynamic Volume® compensates for volume fluctuations in different audio content-for example, during noisy commercial breaks—and adjusts the volume in real time.

#### Audyssey DSX<sup>®</sup> and Dolby<sup>®</sup> Pro Logic<sup>®</sup> IIz for Expanded Surround Sound

Audyssey DSX lets you augment your setup with two Front Wide channels, expanding the width of the soundstage, or two Front Height speakers to add a vertical dimension to movies and games. Dolby Pro Logic IIz offers Front Height channels with 7.1-channel upmixing from stereo sources.

#### App-Controllable Multi-Zone Audio

The TX-NR727 features Powered Zone 2 outputs and Zone 2/3 line-outs. This lets you assign two channels to power audio in a room equipped with speakers. An existing hi-fi system in a third room can also be connected via the line-out, enabling the use of the A/V receiver as a pre-amp and audio server. Control content in all three zones via remote app; play the same song in all zones; or enjoy a different song in every room.

#### Phase-Matching Bass Enhancement

Onkyo's PM Bass optimizes low frequencies while preserving mid-range clarity. It counters phase shifting (which can affect sound quality) by synchronizing frequency timing. The result is deep, well-defined bass that won't overwhelm vocals or strings.

#### Hybrid Standby Power-Saving Mode

HDMI passthrough and network connectivity are maintained while the receiver is powered down. This facilitates use of your TV and other devices without turning on the receiver

### **SPECIFICATIONS**

mp	lifie	r Se	cti	on
	~			_

Amplifier Section	
Power Output	
All Channels	170 W/Ch (6 Ω, 1 kHz, 1% THD,
	I Channel Driven, IEC)
	185W/Ch
•••••••••••••••••••••••••••••••••••••••	(6 Ω, 1 kHz, 1 Channel Driven, JEITA)
Dynamic Power	250 W (3 Ω, Front)
	220 W (4 Ω, Front)
	30 W (8 Ω, Front)
THD+N (Total Harmonic	Distortion + Noise)
	0.08% (20 Hz–20 kHz, Half Power)
Damping Factor	60 (Front, I kHz, 8 Ω)
Input Sensitivity and Impe	
. , .	200 mV/47 kΩ (Line)
	2.5 mV/47 kΩ (Phono MM)
Rated RCA Output Level	and Impedance
	200 mV/2.2 kΩ (Line Out)
Maximum RCA Output L	
i laxinidin itest o'diput E	2.0 V/2.2 k $\Omega$ (Line Out)
Phono Overload	70 mV (MM, 1 kHz, 0.5%)
Frequency Response	5 Hz–100 kHz/+1 dB, -3 dB (Direct Mode)
Tone Control	±10 dB, 30 Hz (Bass)
	±10 dB, 20 kHz (Treble)
Signal-to-Noise Ratio	106 dB (Line, IHF-A)
•••••••••••••••••••••••••••••••••••••••	80 dB(Phono MM, IHF-A)
Speaker Impedance	4 Ω – 16 Ω or 6 Ω – 16 Ω
Video Section	
Input Sensitivity/Output L	evel and Impedance
Video	1.0 Vp–p/75 $\Omega$ (Component Y)
	0.7 Vp-p/75 Ω (Component PB/CB, PR/CR)
	I.0 Vp–p/75 Ω (Composite)
Component Video Freque	ency Response
	5 Hz-100 MHz/+0 dB, -3 dB
Tuner Section	
Tuning Frequency Range	87.5 MHz-108 MHz
AM	522 kHz=1,611 kHz
AU	530 kHz–1,710 kHz
EM/AM Deserve Management	
FM/AM Preset Memory	40 Stations
General	
Power Supply	AC 220-240 V~, 50/60 Hz
Power Consumption	690 W
No-Sound Power Consur	
	240 V: 80 W, 230 V: 75 W
Standby Power Consump	
standby i ower consump	0.2 W
Dimensions (W x H x D)	42E v 17E v 290 mm
Weight	.2 kg
CARTON	
CARTON	
Dimensions $(W \times H \times D)$	570 x 298 x 469 mm

Dimensions (W x H x D) 570 x 298 x 469 mm 14.0 kg (Asian Models : 14.5 kg) Weight

#### Supplied Accessories

 Indoor FM antenna •Antenna isolator\* •AM loop antenna • Speaker cable labels • Speaker set-up microphone • Instruction manual • Quick start guide • Remote controller •AA (R6) batteries\*\* x 2. \*Included with Chinese model only

\*\*Not included with Chinese model



Text on receiver may vary with region.

Due to a policy of continuous product improvement, Onlyo reserves the right to change specifications and appearance without notice. THX, the THX logo, and Select2 are trademarks of THX Ltd.THX and the THX logo are registered in the US, and other jurisdictions. All rights reserved Manufactured under license from Doby Laboratories. Doby, Pro Logic, and the double-D symbol are trademarks of Doby Laboratories. DTS, DTS-HD, the Symbol, & DTS or DTS-HD and the Symbol together are registered trademarks of DTS, Inc. O TDS, I



Onkyo Corporation Kitahama Chuo Bidg. 2-2-22 Kitahama, Chuo-ku, Osaka 541-0041 JAPAN http://www.onkyo.com/ Onkyo Europe Electronics GmbH Lugnitzertarsas 6, 82194 Grobenzell, GERMANY Tei: 49-8142-4280-10 Fax: 49-8142-4288-202 http://www.eu.onkyo.com/ Onkyo Europe Electronics GmbH (UK Branch) Luini 19, Building 6, Cravity Green Building 6, Cravity 6, Crav